




YI 1080p Outdoor PTZ kamera - CZ manuál

Obsah balení



Popis zařízení



Párování kamery

Požadavky:

-Kameru lze připojit pouze k WiFi síti na frekvenci 2.4 GHz (5GHz síť není podporována)

- Nainstalujte si mobilní aplikaci YI Home (ke stažení na Google Play a Apple app store

- Vytvořte si v aplikaci YI Home účet



Instalace

1. Zapoje kameru do elektrické sítě. Vyčkejte na hlasový povel „Welcome to YI Home“ a následně „Waiting to connect“.


2. Přihlašte se do mobilní aplikace a klikněte na „+“. Vyberte kameru ze seznamu nebo naskenujte QR kód na kamerě.

3. Klikněte na „I heard waiting to connect“. Zadejte heslo k Vaší WiFi síti. Po zobrazení QR kódu na displeji telefonu, umístěte displej s QR kódem před čočku kamery.

4. Pokud uslyšíte „Pairing is successful“, párování bylo úspěšně dokončeno.




Nastavení správného úhlu



Umístění kamery


Před vrtáním se ujistěte, že je kamera správně nasměrována a že napájecí kabel je dostatečně dlouhý.

Neumísťte kameru přímo proti slunečnímu svitu.



Pomocí šablony si označte budoucí otvory pro vrtání.

Následně kameru upevněte do zdi pomocí přiložených hmoždinek a šroubů.



Změna Wi-Fi sítě

Pokud potřebujete kameru připojit k jiné wifi síti nebo bylo změněno heslo k původní síti, je nutné kameru opět nově spárovat. V tomto případě postupujte následovně:

1. Pomocí resetovacího pínu krátce stiskněte resetovací tlačítko na hlavě kamery. (vyčkejte na hlasový povel „reset is successful“).
2. Otevřete aplikaci YI Home, původní kameru odstraňte ze spárovaných zařízení a spárujte opět jako nové zařízení.

Upozornění
Čistěte pouze suchým hadříkem. Kamera je určena pro venkovní použití. Postupujte dle manuálu. Používejte pouze originální příslušenství. Vždy používejte aktuální firmware.

Specifikace

Maximální rozlišení: 1920 x 1080
Záběr: 95°
Audio: zabudovaný mikrofon a reproduktor
Modifikace obrazu: 3D Digital Noise Reduction
Wi-Fi: 802.11b/g/n, 2.4 GHz
Bezpečnostní funkce: detekce pohybu, detekce člověka
Noční vidění: IR Cut+Array LED+Bílá LED
Podporované platformy: Android, iOS, Mac, Windows
Šifrování: WEP/WPA/WPA2
Napájení: DC 12V/1A
Spotřeba: 8.4W (max)
Rozsah otáčení: 350° horizontálně, 90° vertikálně
Uložení: Micro SD karta, YI Cloud (placený)
Rozsah teploty pro bezpečné použití: -20°C až 60°C
Odolnost: IP66

FCC COMPLIANCE STATEMENT:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The distance between user and products should be no less than 20cm

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

IC WARNING

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference.
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

The distance between user and products should be no less than 20cm

ADVERTENCIA IC

Cet appareil contient des émetteurs / récepteurs exempts de licence conformes aux RSS (RSS) d'Innovation, Sciences et Développement économique Canada.

Le fonctionnement est soumis aux deux conditions suivantes:

- (1) Cet appareil ne doit pas causer d'interférences.
- (2) Cet appareil doit accepter toutes les interférences, y compris celles susceptibles de provoquer un fonctionnement indésirable de l'appareil.

La distance entre l'utilisateur et de produits ne devrait pas être inférieure à 20cm

Herebywe: Shanghai Xiaoyi Technology Co., Ltd., declares that the radio equipment: YRS-4020 is in compliance with Directive 2014/53/EU.
ProductType: YRS-4020
Wi-Fi: 2.4GHz, 802.11b/g/n
Max RF power: 19.5dBm
Manufacturer: Shanghai Xiaoyi Technology Co., Ltd.
Address: Building 18, NO.55 Chuankou Road, Pudong New District, Shanghai, China
The full text of the EU declaration of conformity is available at the following internet address: <https://kamstore.com/pages/product-certification>

iStage
MI Xiaomi Market



FCC ID: 2AFIB-YRS4020
IC: 20436-YRS4020

iStage.cz
XiaomiMarket.cz